APPLIED KILOVOLTS

Excellence in High Voltage HV Lab Series 477 Data Sheet 4W HIGH VOLTAGE LAB POWER SUPPLY

Application:

Photomultiplier, mass spectrometers, nuclear and medical instrumentation.

- ±0.5kV, ±1kV ±2kV, ±3kV versions
- Input 230 / 115VAC
- Switchable output polarity
- Remote voltage programming or potentiometer setting
- Very low ripple and noise
- Direct reading meter for voltage & current
- Flashover & short circuit protected

brandenburg

477 Series Iss 2 April 2011 Page 1 of 2



Electrical Specification

Order Code	Polarity	Output Voltage	Output Current	Ripple pk-pk	Input Voltage
477-301	Switchable	±500V	8mA	5mV	115V / 230V ac
477-302	Switchable	±1kV	4mA	4mV	115V / 230V ac
477-303	Switchable	±2kV	2mA	2mV	115V / 230V ac
477-304	Switchable	±3kV	1.3mA	5mV	115V / 230V ac

Input	115/230V ac nominal, $\pm 10\%$, 50/60Hz (Switchable 2 ranges). 35VA rating at full load.
Line regulation:	<20ppm over input voltage range.
Load regulation:	<20ppm for zero to full load.
Drift (after 1 hour warm up)	<15ppm in any 15 minute period, <50ppm in any 8 hour period.
Temperature coefficient	<50ppm / °C at maximum rated output.
Control of output (Local)	Front panel 10 turn potentiometer with locking vernier calibration.
Control of output (Remote)	0 to +10V for 0 to 100% rated output voltage, input $Z = 10k$.
Voltage rate of change limit	Selectable from the front panel, ("Ramp"), this limits the rate of change to <2V/mS (at max voltage) reducing the possibility of arcing within the load application or PM tube.
Protection	Current is limited to approximately 110% of maximum rated output until overload condition is removed. Protected against intermittent flashover to ground.
Voltage & current monitor	Direct reading $4\frac{1}{2}$ digit meter, switch selectable between output current and voltage. Available also are buffered monitor outputs for both current and voltage (available from the analogue port on the rear panel, 0 to +10V corresponds to 0 to 100% of the rated output) Accuracy: Voltage 1%. Current =2%.
Auxiliary output	Fixed ±5V and ±15V dc @ 250mA, regulation : ±1%, ripple 10mV pk-pk.
Reference output	+10V.0V ±0.05%, temperature coefficient : <50ppm / °C.

477 Series Iss 2 April 2011. Page 2 of 2

Environmental Specification

Temperature, operating	-10 to +50°C. De-rate above 35°C l	linearly to 80% power at 50°C.	
Temperature, storage	-20 to +75°C.	Humidity (RH) <31°C	80% maximum non-condensing
Pollution category	II	Humidity (RH) >30°C	Decrease linearly to 50% at 40°C

Mechanical Specification

Dimensions	W x H x D: 254 x 109 x 254 mm, inc feet & handle. (10" x 4.25" x 10.0")	∢ , ↓ 254 ↓	
Weight	4kg (9lb) approximately.	 212.73 →	
Input	IEC mains connector on rear panel.	brandenburg Photomultipler Power Supply	1
Control	9 way "D" type on rear panel.		
HV Output	2 off HV SHV connectors on front panel.		
Aux output	Binder 680 series, 7 pins, on front panel.	I O Output On Voltage Adjust	
		Mode m/T V/I Remote ON/OFF -Ve/+Ve ON/OFF Function Meter Control Ramp Polarity Output	98.88
Pin Assignments			
Control (rear) connector pin assignments		Mains Ground Output Aux O/P	
Pin 1	N/C		+
Pin 2	Control input		9
Pin 3	Current monitor		ו '
Pin 4	Voltage monitor		
Pin 5	N/C		
Pin 6	N/C		
Pin 7	Reference output		
Pin 8	Signal ground	Щ Ц	4
Pin 9	N/C		
Aux (front) connector pin assignments		1 [-
Pin 1	-15V		
Pin 2	-5V		4.0
Pin 3	0V		55
Pin 4	+5V		
Pin 5	0V		
Pin 6	+15V	1 1	
Pin 7	0V		
		1 1	
			<u> </u>

Applied Kilovolts Ltd

Woods Way, Goring by Sea, BN12 4QY. United Kingdom. Tel: +44 (0) 1903 708 850 Fax: +44 (0) 1903 708 851 Web: appliedkilovolts.com E-mail: sales@ appliedkilovolts.com

Applied Kilovolts Inc

3 Dodworth Ct. Suite 303, Timonium, MD 21093. USA. Tel: 1 410 308 4828 Fax: 1 410 308 4835 Web: appliedkilovoltsms.com E-mail: nasales@ appliedkilovolts.com